

PRODUCT SHEET - POWER SUPPLY FROM MILLETEKNIK

ECO power supply with battery backup

ECO 24V 1A Mini



ECO 24V 1A Mini is delivered with 230 V mains cable installed.

Name, article number and e-number

Name	Article number	E-number (SV)
ECO 24V 1A Mini	MI01C10324P010B01	52 137 46

Description

Primary switched battery backup, 24 V, 1 A, with two 1.2 Ah batteries.

- [sv] Primärswitchad batteribackup, 24 V, 5 A, med plats för två 28 Ah batterier.
- [sv] Flexibelt - går att utöka reservdrifttiden med extra batteribox med 45 Ah batterier för totalt 73 Ah, (28 + 45 Ah).
- [sv] Standardiserad installation, där alla Sentionkomponenter är inkopplade från fabrik för direkt åtkomst över kopplingsschema (på 20-poliga kopplingsplintar).
- [sv] Monteras på vägg eller i 19" rack.
- [sv] Utökningsmöjligheter inkluderar fler funktioner på ett nytt 20-poligt anslutningskort. Det finns även plats för ytterligare ett dubbel dörrkontrollkort, ett I/O-kort, samt ytterligare säkringskort och liknande.
- [sv] Utökat skydd mot störningar genom åsk/överspanningsskydd på elnätsinkoppling tillsammans med isolationsbrytare.
- [sv] Jackbart kablage på inkopplingsplintar, alla Sentionkorten och övriga (batteribackup-) kort har jackbara plintar.
- [sv] Fjärranslutning över Sention av batteribackupens all status och strömförbrukning i säkerhetssystemet. (Även möjlighet till Unison uppkoppling).
- [sv] Låsbart elskåp, där Larmtablå/MAP sitter bakom låst lock.
- [sv] Alla komponenterna och elkapsling, har var för sig uppfyllt alla EN50131 upp till klass 3

(SSF krav) men är inte provade tillsammans i nuvarande konfiguration.

Area of use

ECO supplies power to access systems, locking systems and other security products in a building that are powered by 12 V DC or 24 V DC. The rectifier in the power supply converts 230 V DC down to 12 V DC or 24 V DC.

Batteries drive, for example, the access system, when the power grid goes down.

Long life, energy efficient and support is available if something goes wrong, now or in 10 years.

Voltage, current and power

Voltage out: 27.3 VDC, (24 V).

Charging current: Depending on the power outlet. Max 1A.

Power outlet: 1 A.

Load outputs

One load output.

Alarm

Alarms are given for: Delayed power failure alarm or low battery voltage.

Protection

Controlled charging of batteries protects against overcharging and extends the life of batteries. Batteries are charged with the most 0.5 A.

Protection against: Deep discharge of batteries, short circuit, overload, overvoltage and overtemperature

Fuses

Load securing: 2 A.

Battery fuse: 10 A.

Indications and communication

Indicator diode shows the status of the device.

Battery and battery type

Two 1.2 Ah batteries.

Battery type: 12 V, AGM lead-acid battery, maintenance-free. Batteries not included.

Backup operating time on batteries

The reserve operating time in battery operation depends on how large a load is connected to the power supply. If the load varies, as with frequent opening of door locks, the time that batteries can continue to power the security system decreases. To get an estimate of reserve operating times see: www.milleteknik.se/Manualer/FaQ/Reservdrifttider/

Enclosure

Dimensions, height x width x depth	Built-in fan	IP class
202 x 148 x 62 mm	No	IP20

Weight

Name	Net weight	Weight incl. packaging
ECO 24V 1A Mini	2.1 kg	2.2 kg

Installation requirements

The device is intended for fixed installation. The unit must be installed indoors, environmental class 1, ambient temperature: +5°C to +40°C. Recommended ambient temperature is +15°C to +25°C (for optimal battery life).

Requirements that the product meets

EMC:	EMC Directive 2014 / 30EU
Electricity:	Low voltage directive: 2014/35 / EU
CE:	CE directive according to: 765/2008



Guarantee

The product has a two-year warranty against manufacturing defects. Batteries and wearing parts are not covered by warranty.

Expandable, options and accessories

The product cannot be expanded.

Manufacturing, lifespan, environmental impact and recycling

Manufactured by Milleteknik in Partille, Sweden.

The product is designed and constructed for a long service life, which reduces the environmental impact. The life of the product (except wearing parts) depends on, among other things, environmental factors, mainly ambient temperature, un-

foreseen load on components such as lightning strikes, external impact, handling errors, etc. Products are recycled, simply because they are modular, by being left at the nearest recycling station or sent back to the manufacturer.¹Contact your distributor for more information.

Link to the latest information

Products and software are subject to updates, you will always find the latest information on our website.

ECO

About this information

All information is published subject to possible errors. This document is updated without notice.

¹Costs incurred in connection with recycling are not reimbursed.