PRODUCT SHEET - POWER SUPPLY FROM MILLETEKNIK

Product image



Name, article number and e-number

Name, article number and email number

Name	Item number	E-number (sv)
Battery Box 24V FLX S	FS010000024BB01	52 13 574

Designation

SSF 1014 approved battery box for 24 V battery backup.

Area of use

Used to extend the backup operating time of power supply / battery backup.

Battery and battery type

4 pieces, 7.2 Ah, battery.

4 pieces, 14 Ah, battery.

2 pieces, 14 Ah, battery.

2 pieces, 20 Ah, battery.

Battery type: 12 V, AGM lead-acid battery, maintenance-free. Batteries not included.

Alarm

Alarms are forwarded to battery backup, which gives an alarm.

Enclosure

Sheet metal cabinet for wall mounting or in a 19" rack cabinet (5 HE). Powder-coated black. Four cable entries on the top and outlet holes on the back. Cable tie holder in enclosure.

Dimensions, fan and IP class.

Dimensions, height x width x depth	Dimensions with packag- ing.
222 x 437 x 145 mm	250 x 490 x 185 mm

Height units, fan and IP class.

HE	Built-in fan	IP class
5	No	IP30

Weight

Weight.

Name	Net weight	Weight incl. packag- ing
Battery box 24V FLX S	3.5 kg	5 kg

Installation requirements

The device is intended for fixed installation. The unit must be installed indoors, environmental class 1, ambient temperature: +5°C to +40°C. Recommended ambient temperature is +15°C to +25°C (for optimal battery life).

Fits

Number of battery boxes that can be connected.

Product series	Enclosure size	Number of battery box- es that can be connec- ted ^{a.}
ECO, NEO, NO- VA	FLX S	1

 $^{^{\}rm a.} \textsc{Connects}$ to 24V battery backups. Cannot be connected to 12 V battery backups.

Requirements that the product meets

The product meets the following requirements.

EMC:	EMC Directive 2014 / 30EU
Electricity:	Low voltage directive: 2014/35 / EU
CE:	CE directive according to: 765/2008
Environment	REACH Regulation: Directive 1907/2006, WEEE Regulation: Directive 20021961E, RoHS Regula- tion: Directive 2015/863





Guarantee

The product has a two-year warranty against manufacturing defects. Batteries and wearing parts are not covered by warranty.

Manufacturing, lifespan, environmental impact and recycling

Manufactured by Milleteknik in Partille, Sweden.

The product is designed for a long service life, which reduces the environmental impact. End-of-

2024-08-20 milleteknik®

life products are handed over to the nearest recycling centre.

Link to the latest information

Products and software are subject to updates, you will always find the latest information on our website.

Battery boxes & battery shelves

About this information

All information is published subject to possible errors. Information is updated without prior notice.

Publication date 2024-08-20